5.4 A Hybrid Thermal-Diffusivity/Resistor-Based Temperature Sensor with a Self-Calibrated Inaccuracy of $\pm 0.25^\circ\text{C}$ (3σ) from -55°C to 125°C

Pan, Sining; Angevare, Jan A.; Makinwa, Kofi A.A.

DOI

[10.1109/ISSCC42613.2021.9366032](https://doi.org/10.1109/ISSCC42613.2021.9366032)

Publication date

2021

Document Version

Final published version

Published in

2021 IEEE International Solid-State Circuits Conference, ISSCC 2021 - Digest of Technical Papers

Citation (APA)

Pan, S., Angevare, J. A., & Makinwa, K. A. A. (2021). 5.4 A Hybrid Thermal-Diffusivity/Resistor-Based Temperature Sensor with a Self-Calibrated Inaccuracy of $\pm 0.25^\circ\text{C}$ (3σ) from -55°C to 125°C . In *2021 IEEE International Solid-State Circuits Conference, ISSCC 2021 - Digest of Technical Papers* (pp. 78-80). [9366032] (Digest of Technical Papers - IEEE International Solid-State Circuits Conference; Vol. 64). Institute of Electrical and Electronics Engineers (IEEE). <https://doi.org/10.1109/ISSCC42613.2021.9366032>

Important note

To cite this publication, please use the final published version (if applicable).
Please check the document version above.

Copyright

Other than for strictly personal use, it is not permitted to download, forward or distribute the text or part of it, without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license such as Creative Commons.

Takedown policy

Please contact us and provide details if you believe this document breaches copyrights.
We will remove access to the work immediately and investigate your claim.

Green Open Access added to TU Delft Institutional Repository

'You share, we take care!' - Taverne project

<https://www.openaccess.nl/en/you-share-we-take-care>

Otherwise as indicated in the copyright section: the publisher is the copyright holder of this work and the author uses the Dutch legislation to make this work public.

5.4 A Hybrid Thermal-Diffusivity/Resistor-Based Temperature Sensor with a Self-Calibrated Inaccuracy of $\pm 0.25^\circ\text{C}$ (3σ) from -55°C to 125°C

Sining Pan, Jan A. Angevare, Kofi A. A. Makinwa

Delft University of Technology, Delft, The Netherlands

Resistor-based temperature sensors can achieve higher resolution and energy-efficiency than traditional BJT-based sensors. To reach similar accuracy, however, they typically require 2-point (2-pt) calibration, compared to the low-cost 1-pt calibration required by BJT-based sensors. This paper presents a hybrid temperature sensor that uses an inherently accurate, but power-hungry, thermal-diffusivity (TD) sensor [1] to self-calibrate an inaccurate, but efficient, resistor-based sensor [2]. The use of an on-chip reference obviates the need for accurate temperature stabilized ovens or oil baths, drastically reducing calibration time and costs. Furthermore, by sharing most of the readout circuitry, the associated area overhead can be reduced. After self-calibration at room temperature (RT, $\sim 25^\circ\text{C}$) and at an elevated temperature ($\sim 85^\circ\text{C}$), the proposed hybrid temperature sensor achieves an inaccuracy of 0.25°C (3σ) from -55°C to 125°C .

A block diagram of the hybrid sensor is shown in Fig. 5.4.1 (top). The resistor-based sensor is built around a Wien-bridge (WB) bandpass filter realized from silicided polysilicon resistors ($R_{WB} = 64\text{k}\Omega$, $\sim 0.3\%/^\circ\text{C}$) and MIM capacitors ($C_{WB} = 5\text{pF}$, $<100\text{ppm}/^\circ\text{C}$). The filter is driven by a square wave at a fixed frequency ($f_{drive} = 500\text{kHz}$) and its temperature-dependent phase shift (ϕ_{WB}) is digitized by a phase-ADC [1]. The TD sensor is built around an electrothermal filter (ETF), whose temperature-dependent phase shift is very well-defined, as it is determined by the thermal diffusivity of highly pure bulk silicon (D_{Si}) and by lithography [1]. As shown in Fig. 5.4.2 (bottom left), the ETF consists of a heater (n+ diffusion) and a thermopile (p+ diffusion/metal thermocouples) in close proximity (heater/hot-junction distance $s = 24\mu\text{m}$). When driven by a fixed-frequency square wave ($f_{drive} = 31.25\text{kHz}$), the heater generates a phase-shifted temperature gradient in the substrate, which is detected by the thermopile and results in a weak output signal. Since the signal amplitude ($\sim 500\mu\text{V}$) is much smaller than that of the WB, it is boosted by an OTA before being applied to the ADC.

As shown in (Fig. 5.4.1, bottom), the phase-ADC consists of a 2nd-order phase-domain delta-sigma modulator (PD Δ ΣM) [2,3]. Choppers in the feedback path of the 1st integrator ($f_{chop} = f_{drive}$) detect the difference between the phase of the input current and the output of a 1-bit phase DAC. Depending on the bitstream output (BS), the choppers are driven by one of two phase references $\phi_{0,1}$ derived from an on-chip clock divider. At steady-state, the average current flowing into the 1st integrator is zero, and so the bitstream average is a digital representation of the input signal's relative phase. In ETF mode, $\phi_{0,1}$ are set to cover an input phase range of 45° to 90° , while in WB mode a range of -22.5° to 22.5° is covered. Although the integrator's $1/f$ noise is mitigated by the choppers, it still dominates that of the WB [3]. In this work, the residual $1/f$ noise in WB mode is suppressed by system-level chopping (CHL, 100Hz), implemented by periodically inverting the polarity of both f_{drive} and the phase DAC selection.

The accuracy of the resistor-based sensor is limited by the spread of the 1st integrator's input impedance Z_{in} , as it is effectively in series with the WB. The 1st integrator is based on a Miller-compensated opamp, and so Z_{in} can be reduced by either increasing its unity-gain BW or by increasing the size of the integration capacitors ($= 23\text{pF}$). In this work, the former is efficiently boosted by using a buffer to reduce the opamp's capacitive load (a switched-capacitor CMFB circuit and the 2nd stage), as shown in Fig. 5.4.1 (bottom-left). The buffer (a PMOS source-follower) consumes only $1.1\mu\text{A}$ compared to the opamp's $16\mu\text{A}$, but allows the opamp's BW to be doubled.

To facilitate low-cost calibration, the ETF needs to achieve a resolution ($<20\text{mK}$) commensurate with its target accuracy (0.2°C) in a reasonable conversion time ($T_{conv} \leq 1\text{s}$). Compared to [1], the ETF's resistance and, thus, its dominant thermal noise are significantly reduced by using an octagonal layout [4] (Fig. 5.4.2, bottom left). The associated OTA (gm $\sim 1.8\text{mS}$, BW $\sim 600\text{MHz}$) is designed so that its noise is lower than that of the ETF, and so that its phase shift contributes negligible temperature error ($<0.03^\circ\text{C}$). After chopping, the OTA's offset appears as ripple at the output of the 1st integrator, and so to prevent it from clipping, the OTA is auto-zeroed [1].

In this work, a telescopic OTA is used (Fig. 5.4.2), which is more area and power-efficient than the folded-cascode OTA used in [1]. To minimize its own $1/f$ noise, PMOS input transistors and resistor-degenerated NMOS current sources are used. An auxiliary OTA

branch (gm $\sim 0.06\text{mS}$) is used for auto-zeroing. Its hold capacitors ($C_H \sim 7\text{pF}$) are large enough to ensure that auto-zeroing is only needed at the start of each CHL phase (every 0.5s).

The hybrid sensor was fabricated in a standard $0.18\mu\text{m}$ CMOS process (Fig. 5.4.7). In ETF mode, the sensor consumes 5.1mW (4.2mW heater, 0.9mW analog, and $0.6\mu\text{W}$ digital) from a 1.8V supply. In WB mode, when both the heater and the OTA are turned off, its power consumption drops to $66\mu\text{W}$ at room temperature (RT). The sensor has an active area of 0.2mm^2 , with $\sim 40\%$ occupied by the ETF and OTA. For flexibility, the decimation filters (sinc^2) are implemented off-chip. Four WB sensors and four TD sensor variants were implemented on the same chip.

After ceramic DIL packaging, 20 samples from one wafer were characterized in a temperature-controlled oven from -55°C to 125°C . To limit the effect of the oven's temperature drift, the samples were mounted in good thermal contact with a large aluminum block. Furthermore, the resolution of the WB sensor was determined by making differential measurements on two sensors on the same die [3]. As shown in Fig. 5.4.4 (right), the WB sensor achieves $450\mu\text{K}_{\text{rms}}$ resolution with $T_{conv} = 10\text{ms}$, which corresponds to a 0.13pJ-K^2 resolution FoM. After enabling system-level chopping ($f_{CHL} = 100\text{Hz}$), its $1/f$ noise corner drops from $\sim 1\text{Hz}$ to below 10mHz (Fig. 5.4.4, left). In comparison, the ETF sensor's resolution is only 15mK with $T_{conv} = 1\text{s}$ and $f_{CHL} = 1\text{Hz}$, which corresponds to a resolution FoM of $1.2\mu\text{J-K}^2$. However, this still represents a $6\times$ improvement on [1].

As shown in Fig. 5.4.3, top, the phase shift of the TD sensor varies by $\sim 30^\circ$ ($f_{drive} = 31.25\text{kHz}$), while that of the WB sensor varies by $\sim 23^\circ$ ($f_{drive} = 500\text{kHz}$). The ETF sensor achieves a no-trim inaccuracy of 0.2°C (3σ) around RT (Fig. 5.4.3, bottom left), which is similar to that of [1]. On the other hand, the WB sensor's no-trim inaccuracy is larger than 10°C . After mapping the BS output to resistance, the WB sensor achieves 0.5°C (3σ) inaccuracy after a correlated 1-pt trim [2] (Fig. 5.4.5, top left). After a 2-pt trim at -35°C and 105°C this improves to 0.03°C (3σ), which represents the state-of-the-art (Fig. 5.4.5, top right). However, this requires an external reference sensor. Using the ETF as an internal reference (at RT and $\sim 85^\circ\text{C}$) results in an inaccuracy of 0.25°C (3σ), Fig. 5.4.5 (bottom right). For somewhat better inaccuracy 0.15°C (3σ), (Fig. 5.4.5, bottom left), an external reference can be used to calibrate the hybrid sensor at RT, allowing the TD sensor to be offset-trimmed before it is used to calibrate the WB sensor at another elevated, but not well defined, temperature (85°C).

Figure 5.4.6 summarises the performance of the proposed hybrid sensor and compares it with state-of-the-art BJT- [5,6], resistor- [2,3], and ETF- [1] based sensors. The WB sensor achieves a state-of-the-art relative inaccuracy after a 2-pt trim, the lowest reported $1/f$ noise corner, and a competitive resolution FoM. It obtains a 3σ inaccuracy of 0.25°C from -55°C to 125°C after a cost-effective self-calibration, which is comparable to that of BJT-based sensors [5,6]. In contrast to BJT-based sensors, however, the scalability of TD sensors means that even better performance can be expected in nanometer CMOS processes.

References:

- [1] C.P.L. van Vroonhoven and K.A.A. Makinwa, "A Thermal-Diffusivity-Based Temperature Sensor with an Untrimmed Inaccuracy of $\pm 0.2^\circ\text{C}$ (3σ) from -55 to 125°C ," *ISSCC*, pp. 314-315, Feb. 2010.
- [2] S. Pan et al., "A Resistor-Based Temperature Sensor with a 0.13pJ-K^2 Resolution FOM," *IEEE JSSC*, vol. 53, no. 1, pp. 163-174, Jan. 2018.
- [3] S. Pan et al., "A 0.12mm^2 Wien-Bridge Temperature Sensor with 0.1°C (3σ) Inaccuracy from -40°C to 180°C ," *ISSCC*, pp. 184-185, Feb. 2019.
- [4] U. Sonmez et al., "Compact Thermal-Diffusivity-Based Temperature Sensors in 40-nm CMOS for SoC Thermal Monitoring," *IEEE JSSC*, vol. 52, no. 3, pp. 834-843, March 2017.
- [5] B. Yousefzadeh and K.A.A. Makinwa, "A BJT-Based Temperature Sensor with a Packaging-Robust Inaccuracy of $\pm 0.3^\circ\text{C}$ (3σ) from -55°C to $+125^\circ\text{C}$ After Heater-Assisted Voltage Calibration," *ISSCC*, pp. 162-163, Feb. 2017.
- [6] K. Sourl et al., "A CMOS Temperature Sensor with a Voltage-Calibrated Inaccuracy of $\pm 0.15^\circ\text{C}$ (3σ) From -55 to 125°C ," *IEEE JSSC*, vol. 48, no. 1, pp. 292-301, Jan. 2013.

Figure 5.4.1: Simplified schematic of the hybrid sensor (top), phase-domain delta-sigma modulator (bottom right) and the use of a buffer to extend the 1st-stage opamp's bandwidth (bottom left).

Figure 5.4.3: Phase output characteristic (top) and no-trim temperature inaccuracy (bottom) of the ETF (left, 20 samples) and WB (right, 80 samples) temperature sensors.

Figure 5.4.5: WB inaccuracy (80 samples) after a correlation-based 1-pt trim (top left), a 2-pt trim at -35°C and 105°C (top right), a 1-pt trim at 25°C and a 1-pt self-calibration at 85°C (bottom left), and a 2-pt self-calibration at 25°C and 85°C (bottom right).

Figure 5.4.2: Octagonal layout of the thermopile ETF (bottom left) and simplified schematic of the auto-zeroed (AZ) OTA (right).

Figure 5.4.4: Power spectral densities of both sensors (left) and resolution vs. conversion time (right). The WB sensor's 1/f noise is suppressed by system-level chopping (CHL).

	van Vroonhoven ISSCC'10 [1]	Souri JSSC'13 [6]	Yousefzadeh ISSCC'17 [5]	Pan JSSC'18 [2]	Pan ISSCC'19 [3]	This work	
Sensor type	Thermal diffusion	BJT	BJT	Resistor WB	Resistor WB	Thermal diffusion	Resistor WB
Technology	0.18μm	0.16μm	0.16μm	0.18μm	0.18μm	0.18μm	
Area [mm ²]	0.18	0.08	0.17	0.72	0.12	0.20	
Temp. range	-55°C to 125°C	-55°C to 125°C	-55°C to 125°C	-40°C to 85°C	-40°C to 180°C	-15°C to 105°C	-55°C to 125°C
3σ inaccuracy [°C]	0.2	0.15 ^a	0.3 ^b	0.03	0.1	0.2	0.25
(Temp. trimming points ^a)	(0)	(0)	(0)	(2)	(2)	(0)	(2)
1/f noise corner [Hz]	—	—	—	<1	<1	—	<0.01
Power [mW]	3	0.005	0.007	0.16	0.052	5.1	0.066
Conv. time [ms]	6250	5.3	5	5	10	1000	10
Resolution [mK]	20	20	15	0.41	0.46	15	0.45
Resolution FoM [pJ·K ⁻¹] ^c	7.5M	11	7.8	0.13	0.11	1.2M	0.13

^a Trimming points that require accurate temperature information.

^b Requires a voltage reference

^c FoM = Energy / Conversion x (Resolution)².

Figure 5.4.6: Performance summary and comparison with previous work.

Figure 5.4.7: Die micrograph of the fabricated sensor.